


The 2-Way Universal LCD Keyfob that puts the power of a keypad in your pocket.

NAPCO's Pocket-Size, 2-Way LCD Keyfob That Works With All Major Alarm Panel Brands



2WAYUNIVKF



NAPCO

2-Way Universal LCD Keyfob



NAPCO introduces the new 2WAY-UNIVKE, the security industry's first and only universal bi-directional keyfob with LCD status display and integral mini sounder, supported by a revolutionary dedicated receiver.

Designed to be compatible with most major control panel brands, including NAPCO's Gemini and Magnum, and others such as ADEMCO, DSC, ITI and more, this 2-Way Keyfob is super-miniaturized for portability yet packs tremendous consumer appeal and sales potential.

System Status is indicated with 8 intuitive ICONS (a lock, a house, a flame, etc.) on the LCD display, and corresponding beep sequences on its mini sounder. Providing both easily understood visual and audible

feedback, the user always knows with certainty that the system has carried out their command. Plus, the product includes rolling code for still greater consumer confidence.

In addition to the many standard commands it can send to the system, it can also control up to 2 groups of lighting control, such as X-10, and up to 2 separate Garage Doors.

Napco 2WAY-UNIVKE keyfobs are also sold in a kit with dedicated 2-way receiver, Model 2WAY-UNIVKEKIT. Each receiver supports up to 7 keyfobs.

Easy LCD ICON Indicators

Burglar Alarm	Disarmed - Zones Faulted
Fire Alarm	Disarmed - System Ready
Armed - Away	Transmit
Armed - Stay	System Trouble
Armed - Zones Bypassed	Transmitter Low Battery

Note: Grey indicates pulsing icon



SPECIFICATIONS

COMMAND BUTTONS

- STATUS
 - Press to display current system status
 - Hold down Status button to turn on Status Mode to continually indicate change in alarm status visually & audibly
- ON/OFF
 - Press to Arm "Away"
 - Hold Down 2 seconds to Arm "Stay"
- PANIC
 - Hold Down 2 seconds to activate panic alarm
- GARAGE DOOR
 - Press to activate Garage Door 1 control (on-board Relay 1)
 - Hold Down for 2 seconds to either:
 - A. Toggle on Relay Control Group 2 and on-board Relay 2 (default operation).
 - B. Activate Garage Door 2 control (on-board Relay 2) (programmable).



- ON/OFF and DOOR
 - Press simultaneously to toggle on Relay Control Group 1 and on-board Relay 1.

- Dimensions: 1.6" x 2.5" x 0.70" (H x W x D)
- Weight: 1 oz.
- Battery: 1 AAA alkaline cell (User replaceable)
- Expected battery life: 3 Years
- RF Range: 1,000 feet (open air)
- Max # of Keyfobs: Up to 7 Keyfobs supported by the receiver.
- CONNECTION: 2WAY-UNIVKE will operate on either the panel bus or its keyswitch input depending on control panel brand (consult WH1024 for details). With bus connection (e.g., with Gemini and others), the keyfob uses no zones, and up to 7 keyfobs are independently logged. With keyswitch connection, keyfob uses one zone for keyswitch and one zone for panic, if desired.



NAPCO SECURITY GROUP

333 BAYVIEW AVENUE • AMITYVILLE, NY 11701 • 1-800-645-9445 • (631) 842-9400

FAX: (631) 789-3383 • www.napcosecurity.com

Preliminary specifications subject to change. ©2009/2010 Napco • Pat. Pending