



Congratulations on your purchase of a StarLink SL-1FD-T

When activating Napco's Full Data Alarm Communicator, be sure and only choose options which enable it to provide full data alarm reporting. Please read the Quick Guide below for choosing the right ones:

1. REGISTER as a first-time dealer at www.napcostarlink.net.
- Request a login & (numeric) pin code /password.
You will receive an email confirmation of same from Napco Customer Service.

StarLink Customer Login

Enter your 10 digit ID number and password to login to the StarLink website.

Enter Identification #:
Enter Password:

StarLink Registration Form

Note: * Items are required, completing all items will further speed up the full registration process.

*Company:
*Contact Name:
Title:
*Address 1:
Address 2:
*City, State Zip:
*Email:
Phone:
Fax:
*Password:
Note: Your password will be your 10 digit phone number, without any dashes or spaces.
Comments:

2. LOG IN at www.napcostarlink.net, entering your 10 digit dealer identification number and password (pin code)



3. PURCHASE ANNUAL SERVICE SUBSCRIPTION: To purchase the mandatory annual subscription service for this radio, call NAPCO Customer Service at 1-800-645-9445 with any major credit card. - MANDATORY

4. ENTER the radio ID number, on the Welcome screen, from the base of the unit, in the "Assign" box, on the right side of the screen and Click "Assign"

Edit Subscriber Unit ID# 252408

[Click here to exit without saving changes.](#)

Subscriber Unit Info:

Subscriber Name:	<input type="text"/>
Subscriber Tel. Num.:	<input type="text"/>
Subscriber Address:	<input type="text"/>
Subscriber City:	<input type="text"/>
Subscriber State:	<input type="text"/>
Subscriber Zip:	<input type="text"/>

- Account:
-
-
-
-
-

5. On the Edit Subscriber Unit ID# screen, Enter all your Subscriber Unit info. for the radio whose number appears at the top of the page - MANDATORY



ENTER all your Central Station Reporting info. for the primary receiver in the first block entitled "Download Path Info. (First Report)" - MANDATORY

6.

- Choose **ONLY** Contact ID or Pulse 4/2, in the pull down menus!!!

Download Path Info. (First Report)		
	Digital ID:	Digital Receiver #:
Primary:	<input type="text"/>	<input type="text"/>
Secondary:	<input type="text"/>	<input type="text"/>
Logging:	<input type="text"/>	<input type="text"/>
Report Fail:	<input type="text"/>	<input type="text"/>
Supervise Fail:	<input type="text"/>	<input type="text"/>

Download Path Info. (Second Report)		
	Digital ID:	Digital Receiver #:
Primary:	<input type="text"/>	<input type="text"/>
Secondary:	<input type="text"/>	<input type="text"/>
Logging:	<input type="text"/>	<input type="text"/>
Report Fail:	<input type="text"/>	<input type="text"/>
Supervise Fail:	<input type="text"/>	<input type="text"/>

OPTIONAL: Enter same type of info. in second block, for secondary Central Station Reporting info. This block is entitled "Download Path Info. (Second Report)"

7.

- Choose **ONLY** Contact ID or Pulse 4/2, in the pull down menus!!!

8.

BYPASS or SKIP the 3rd data block entitled "Reporting Code Template", because your unit is full-data reporting.

Reporting Code Template					
SC Code:	Pulse:	Contact ID:	Event:	Zone:	Condition:
1	1B	100	351	Input 1	Report
2	2B	120	352	Input 2	Report
3	3B	130	353	Input 3	Report
SC Fire (C)	1C	110	354	Fire	Report
SC Burglary (B)	2C	130	355	Burglary	Report
Radio Supervisory Failure	9B	327	356	Supervisory Fail	Report
SC Report Failure	FF			Report Fail	No Report

*SC Stands for Smart Channel. Download path format determines which reporting code column will be used. If you select the Pulsed 42 Download path format, it will not be transmitted if only one digit is entered in the reporting code column. If you select the Pulsed 31 or 41 Download path format, and two digits are entered it will transmit the first digit in the reporting code.

Save Changes Reset Changes

9.

Just Click on the bottom of screen where the words "SAVE CHANGES" appear

DESCRIBE what action or change you made to this account for your reference, in the pop-up dialogue box, for example "activating account", etc. Click the "OK" at the top of the dialogue box to save all and finish.

Save Changes	Reset Changes
Click here to exit without saving changes.	
<div> <div>Explorer User Prompt</div> <div>Script Prompt</div> <div>Enter a brief description of the changes made.</div> <div>OK</div> <div>Cancel</div> </div>	

10.

Click on the words "SAVE CHANGES" on the bottom of the screen. - MANDATORY

11.

"SUBSCRIBER UNIT SAVED" screen will now appear
CONGRATULATIONS your radio activation enrollment info. is complete and first-time test signals can be sent to field-test the installation.

Subscriber Unit Saved	
Subscriber 251905 has been saved.	
Subscriber Unit Info.	
Status:	Online
Supervisory (Time):	1 December 1997
Subscriber ID:	031020000
Subscriber Name:	000000
Subscriber Unit:	000000
Subscriber Address:	000000
Subscriber City:	000000
Subscriber State:	00
Subscriber Zip:	000000
Download Path Info.	
First Report:	
Digital ID:	100
Digital Receiver #:	351
Primary:	100
Secondary:	120
Logging:	130
Report Fail:	110
Supervise Fail:	130
Second Report:	
Digital ID:	100
Digital Receiver #:	352
Primary:	100
Secondary:	120
Logging:	130
Report Fail:	110
Supervise Fail:	130
Reporting Code	