



The All-in-One Smart Panel You Asked For
A FULL LINE OF SECURITY & SMART HOME PRO OPTIONS

Wireless Smoke/CO Detector - PSMKCO

2 in 1 Detection

The Prima dual-function Wireless Smoke and Carbon Monoxide detector, monitors both smoke and carbon monoxide, alerting you with a 85dB alarm. Prima's Wireless Smoke/CO Detector features a self-diagnostic test for CO alarms and low battery/malfunction warnings, ensuring your safety with minimal maintenance. The unit operates on a 3V lithium battery and covers a wireless range of up to 492 feet. The location of the Sensor can have a significant effect on range. In open/unobstructed situations, the transmitter range may be greater. In adverse wireless conditions, you may encounter a decrease in range.



TECHNICAL SPECIFICATIONS

- 2 in 1 Detection – Smoke & Carbon Monoxide
- 433 MHz Long Range Wireless
- Wireless Signal Range: up to 492 ft.*, open air, with Security Panel
- Powerful 85dB Sounder & 3 LED indicators
- Encryption: Yes, 1-way
- Standby Current: 42 uA
- Active Current – RF Only: 8 mA
- Active Current – CO Alarm: 14.87 mA
- Active Current – Smoke Alarm: 74.17 mA
- Operating Temperature: 32° to 120.2°F (0° to 49°C)
- Relative Humidity (Storage): 80% Max. non-condensing
- Tamper Supervised
- Self-Diagnostic Test & E.O.L. Signal for CO
- Low Battery/Trouble Sounder & Indicator
- Silence & Alarm Test Button
- Low power consumption
- Long Life CR123A 3V Lithium Battery Supplied
- Compliances: ETL Listed to UL268, UL2075. FCC